

The novel strategy of electrical arc furnace design and control approach for voltage flicker investigation

Mohan P. Thakre¹, Pawan C. Tapre², Deepak P. Kadam³, Mousam Sharma⁴, Sunil Somnath Kadlag⁵, Yogesh Vilas Mahadik⁶

¹Department of Electrical Engineering, Shri Vithal Education & Research Institute (SVERI's) College of Engineering, Solapur, India

²Department of Electrical Engineering, SND College of Engineering Education & Research Center, Nashik, India

³Department of Electrical Engineering, MET Institute of Engineering, Nashik, India

⁴Department of Electrical Engineering, Bhilai Institute of Technology, Bhilai, India

⁵Department of Electrical Engineering, Amrutvahini College of Engineering, Sangamner, India

⁶Department of Electrical Engineering, Government Polytechnic, Malvan, India

Article Info

Article history:

Received Sep 25, 2022

Revised Jan 6, 2023

Accepted Feb 23, 2023

Keywords:

Arc furnace

Electric arc furnace

Flicker

Harmonic

Power quality

ABSTRACT

Voltage flickers and harmonics are power quality (PQ) problems in the electric system during a variation and arc furnace (AF) adaptability. AF creations must determine a harmonic and flicker. This article evaluates complex AF systems. This article presents a newly established time domain (TD) static become to on an AF's V-I attributes (VIA). Static arc configurations are useful for harmonic analyses, but dynamic methods are needed for PQ studies, especially voltage flicker analysis. The MATLAB-based dynamic AF configuration is simulated for four different configurations. A response with configurations 1 and 4 varies from the real AF outcomes. The simulation results and numerical finding shows that configurations 2 and 3 are much more appropriate and produce better results for minimum 3rd harmonics for arc current, arc voltage, and point of common coupling (PCC) voltage. The novelty of this configuration is that the energy transferred to the load by the AF during the cycle of operation has been identified, making the developed scheme more reliable and dependent on the load's operational conditions. After that, effective applications of these configurations and other configurations' accuracy should be clarified.

This is an open access article under the [CC BY-SA](https://creativecommons.org/licenses/by-sa/4.0/) license.



Corresponding Author:

Mohan P. Thakre

Department of Electrical Engineering

Shri Vithal Education & Research Institute (SVERI) College of Engineering

Pandharpur, Solapur, Maharashtra, India

Email: mohanthakre@gmail.com

1. INTRODUCTION

The arc furnace (AF) appears to become an unstable, non-linearity, and time-varying load which could produce several power quality (PQ) problems throughout the power grid. Instability, harmonics, inter-harmonics, and voltage flicker may result from the AF load. To comprehend the effect of an AF [1], [2] the dependable three-phase AF framework for harmonic analysis and flicker compensation is developed. Even though arc melting is a static probabilistic structure, making a proper simple technology for AF load seems to be challenging. The melting or refining materials, the placement of the membrane, the influence of an electrode arm, as well as the impedance of a supply line appear to be variables that influence the execution of the AF [3]-[5]. As a result, the characterization of an AF load is responsible for key factors: i.e. arc voltage (Varc), arc current (Iarc) as well as arc length (Larc).

The various AF configurations can be divided into "time domain (TD)" and "frequency domain (FD)" methods. The FD methodology takes into account the V_{arc} as well as the I_{arc} of its harmonic [6], [7]. A power system circuit model is established between each input frequency, and an AF has been designed as a voltage source at the same frequency [8], [9]. The overall system action is noted by superimposing a control performance at each frequency [10], [11]. Another requirement for the FD analysis is predefined V_{arc} and current calculated data to obtain a harmonic voltage source methodology. One such configuration has been used without evaluation. A few descriptions [12]-[15] have formed the harmonic domain simulation model of a nonlinear differential approximation. Such approximations support a relationship between the arc radius and the I_{arc} . These other frameworks include some testing procedures to evaluate the execution of the AF. Because of all of these intriguing new and imprecise variables, such designs aren't widely used. Although the electrical arc is a non-linear concept with varying times, a summary of its behaviour and attitude in the TD is simpler than in the FD [13]. TD methodologies are now the most common type of flicker investigation throughout electric arc furnaces (EAF). VIA and equivalent circuit methods (ECM) are the two types of TD methodologies.

The ECM techniques are being learned through arc deployment; the periodic alteration of the V_{arc} , as well as the resistance shown by the arc, could have been used to determine the AF configuration [16], [17]. Much more standardization in the estimation of the prototype could affect the prediction's ability [18]. The VIC techniques usually focus on the AF's VIA derived from correlation, respectively V_{arc} and I_{arc} using the VIA. Such a technique has been commonly used to configure the static and dynamic execution of the EAF [19]. Numerical AF configurations with differing degrees of accuracy are extracted from the VIA. Numerical simulations also will be presented [20]-[23]. The dynamic response of the revised flicker simulations is then addressed. A unique TD framework for the AF is discussed thoroughly. The new technique is being analyzed by MATLAB simulation software [24]-[28].

The structure of an article is as follows; sections 2 define the EAF's static and dynamic execution. It also describes the proposed flicker analysis technique with EAF. Section 3 presents the results of the system modelling for simulation used in the study. Finally, in section 4, AF is represented for both frequency and TD, with the conclusion.

2. STATIC CONFIGURATIONS AND METHOD

Figure 1 represents the real VIA and the piecewise linear configuration of the AF [20]-[22]. The arc ignition (V_{ig}) and extinction voltage (V_{ex}) have been based on the length of a V_{ig} , mostly during AF operation. Besides estimating the real VIA of the AF, different TD structures were given by the following.




Figure 1. Real and piecewise linear estimation of the VIA of the AF load

2.1. Configuration 1

Two linear functions are used to compute the AF's true configuration. Let R_1 , R_2 be the slopes of its OA and AB boundaries, respectively. As a result, throughout this approach, the link between V_{arc} and current for a single cycle is explained as (1)-(3). Figure 2 illustrates the simulated VIA of configuration 1 using MATLAB simulation software.

$$v = \begin{cases} R_1 i & \dots \dots \dots -i_1 \leq i < i_1 \\ R_2 i + v_{ig} \left(1 - \frac{R_2}{R_1}\right) & \dots \dots \dots i_1 < i \leq i_2 \\ R_2 i - V_{ig} \left(1 - \frac{R_2}{R_1}\right) & \dots \dots \dots -i_2 \leq i < -i_1 \end{cases} \quad (1)$$

Where

$$i_1 = \frac{v_{ig}}{R_1} \quad (2)$$

$$i_2 = \frac{v_{ex}}{R_2} - v_{ig} \left(\frac{1}{R_2} - \frac{1}{R_1}\right) \quad (3)$$




Figure 2. VIA of configuration 1

2.2. Configuration 2

Apart from looking at some of the attributes in further additional detail, a slightly more precise non-linear estimation arrangement can be formed. The overall VIA of the non-linear setup 2 [1] is depicted in Figure 3. Throughout its configuration, an arc melting system is divided into three sections. The amplitude of an applied voltage is rise from its V_{ex} to the V_{ig} in the first section. The AF acts as just a resistor in this segment [23], and the I_{arc} modifies its directivity from $-i_3$ to i_1 . The second section depicts the start of the arc melting. As this exponential voltage throughout the membrane changes dramatically, the V_{arc} decreases from V_{ig} to V_{st} , as well as the I_{arc} gradually increases from i_1 to i_2 . The third part appears to be the arc's normal melting procedure. V_{arc} drops from V_{ex} in a linear, slow, and efficient manner. In (4) and (5) contain the formulas that demonstrate such differences. Figure 3 illustrates the modelling VIA of configuration 3 MATLAB/Simulink software was used.




Figure 3. VIA of configuration 2

$$v = \begin{cases} R_1 i & \dots\dots\dots (-i_3 \leq i < i_1, inc) or \\ & \dots\dots\dots (-i_1 \leq i < i_1, dec) \\ v_{st} + (v_{ig} - v_{st}) \exp((i_1 - i)/i_T) & \dots\dots\dots i_1 \leq i < i_2, inc \\ v_{st} + (i - i_2)R_2 & \dots\dots\dots i_1 \geq i_2, inc \\ v_{ex} + (i - i_3)R_3 & \dots\dots\dots i_1 \geq i_3, dec \\ -v_{st} + (v_{st} - v_{ig}) \exp((i_1 + i)/i_T) & \dots\dots\dots -i_2 \leq i < -i_1, dec \\ -v_{st} + (i_1 + i_2)R_2 & \dots\dots\dots i < -i_2, dec \\ -v_{ex} + (i + i_3)R_3 & \dots\dots\dots i < -i_3, inc \end{cases} \quad (4)$$

Within which R_1 , R_2 , and R_3 are just the slopes of the respective segments.

$$i_1 = \frac{v_{ig}}{R_1}, i_T = 1.5i_1, i_2 = 3i_1, i_3 = \frac{v_{ex}}{R_1} \quad (5)$$

2.3. Configuration 3

An arc melting mechanism can indeed be classified into three types by analyzing an AF's actual VIA. In this setup, a few other assumptions have been made under these three stages, as explained in [19]. Over the first duration, an arc initiates to resurface from destruction. Whenever the V_{arc} drops to zero, this same I_{arc} also attains its own zero point of intersection. Even though V_{arc} reaches the resignation voltage V_{ig} , the equivalent circuit remains open. The low current will have flowed parallel to an arc V_{ia} the foamy slag. The foamy slag does have a constant resistance of R_g , as well as the resignation voltage has been presumed to be proportional to the reciprocal of the arc [18].

The arc was formed in the second quarter. At the beginning of the arc melting, a transient method tends to appear in the waveform. The V_{arc} rate varies from V_{ig} to the constant V_d , which is unusual. One such phase is almost certainly defined as either an exponential function with such a time constant of T_1 . The arc begins to leave the area during the third period. Except for an indicated extent after the arc is extinguished, the V_{arc} begins to deteriorate smoothly. This is presumed that the mechanism is mentioned by an exponential with a time constant T_2 .

Following all of the preceding examples, the EAF was developed as a current-controlled non-linear resistance, as shown in Figure 4. Numerical depictions of the EAF shall be prepared by (6). The I-R graph can be seen in Figure 5 and the expression of V_{ig} current and instantaneous voltage is shown in (7).

$$R_a = \begin{cases} R_1 & \dots\dots\dots; \left| 0 \leq I < i_{ig}, \frac{dI}{dt} > 0 \right. \\ \frac{[v_d + (v_{ig} - v_d) \exp(-(I - i_{ig})/\tau_1)]}{I} & \dots\dots; I \geq i_{ig}, \frac{dI}{dt} > 0 \\ \frac{[v_t + (v_{ig} - v_t) \exp(-I/\tau_2)]}{I + i_{ig}} & \dots\dots\dots; \frac{dI}{dt} < 0 \end{cases} \quad (6)$$

Where $I = |i(t)|$, $v_{ig} = 1.15v_d$

$$i_{ig} = \frac{v_{ig}}{R_1}, V_t = \left[\frac{i_{ig} \max}{I_{\max}} \right] v_d \quad (7)$$




Figure 4. VIA of configuration 3




Figure 5. Arc I-R graph

2.4. Configuration 4

A different type of arrangement, as well as simplicity of the real attribute, has been seen in Figure 6 [8]-[12]. So, the V_{arc} alters polarity so rapidly, one such configuration ignores the increasing voltage time, resulting in a huge change in the V_{arc} so when the I_{arc} has been at nil. Thus, the ideal cycle of the VIC has been demonstrated as (8):

$$v = \text{sign}(i)[v_{at} + \frac{c}{d+|i|}] \quad (8)$$

Let " l " be the Larc, A and B are the coefficients from the experimental formula, then:

$$v_{at} = A + B.l \quad (9)$$

Where, V_{at} reflects the AF operating condition as indicated in (8) and (9).

Voltage flicker has become a stochastic and time-variation phenomenon that occurs in RMS voltage variation in the range of frequencies (0.5-25 Hz). A dynamic AF setup is done [24] to assess the flicker produced by AF. The slop, including its VIA throughout Figure 1 has been modified mostly as a sinusoidal wave to construct dynamic characteristics of an AF which uses different structures. These same dynamic load implementations throughout configurations 1, 2, and 3 take into account periodic changes in the R_{arc} to the rating provided on every setup. Throughout the scenario of sinusoidal variance, the R_{arc} is defined when:

$$R_1(t) = R_1(1 + m \sin(w_f t)) \quad (10)$$

In which R_1 is just the constant resistance of an AF when the arc is off but the EAF acts as an open circuit, $1/R_f=5-007$ is just the frequency of the flicker and the coefficient of modulation. Its voltage throughout (8) had already influenced a different loading configuration in setup 4, so the voltage could've been considered in (11):

$$v_{at}(t) = v_{at}(1 + m \sin(w_f t)) \quad (11)$$




Figure 6. VIA of configuration 4

2.5. Proposed flicker analysis technique with EAF

The dynamic AF configuration has been produced by (10), which is an R_1 change in the aspects discussed (say R_1 modulation). Concerning the AF's VIC, this same R_1 has been associated with the low current cycle of a furnace cycle. The R_2 has been associated with the effective phase of the cycle; then the more current passes through the membranes, the more flickers are intended.

If using R_2 modulation to produce the furnace's dynamic behaviour, many flickers have been produced, and the results appear to be relevant to the actual ones. Whereas more power has been obtained from the furnace throughout portion AB of a VIC, many flickers have been assumed, and the use of R_1 transduction contributes to an inaccurate produced flicker scenario. When the duration of the arc changes, a large proportion of flickers are produced, so this timeframe is in portion AB of the attribute. The dynamic configuration of a combustion chamber could therefore be produced by modulating R_2 , as shown in (12):

$$R_2(t) = R_2(1 + m \sin(w_f t)) \quad (12)$$

3. RESULTS AND DISCUSSION

When comparing AF configurations, a simple AF system has been developed in some kind of single phase. The system's configuration is depicted in Figure 7. All across Figure 7, the system's impedance would be stipulated as mentioned earlier: the point of common coupling (PCC) bus denotes a PCC, and the AF bus did appear to become the low voltage side of the transformer, the impedance of it has been supplied. Table 1 includes the modeling schematic in Figure 8 and also the control variables as well as configurations by each structural system.




Figure 7. Study system of AF

Table 1. Study system parameters with EAF

Study system	$V=566$ V; $f=60$ Hz; $Z_s=0.3366+j3.22$ m Ω ; $Z_l=0.0528+j0.468$ m Ω
Configuration 1	$V_{ig}=350.75$ V; $V_{ex}=289.75$ V; $i_1=7015$ A; $i_2=87.278$ kA; $R_1=0.5$ Ω ; $R_2=-0.76$ m Ω
Configuration 2	$V_{ig}=350.75$ V; $R_1=0.5$ Ω ; $V_{at}=350.75$ V; $V_{ex}=289.75$ V; $R_2=-0.76$ m Ω ; $R_3=-0.39$ m Ω
Configuration 3	$V_{ig}=350.75$ V; $I_{max}=100$ kA; $\tau_1=0.01$ sec; $\tau_2=0.02$ sec
Configuration 4	$V_{at}=289.75$ V; $C=1.68$ MW, $D=20.65$ kA




Figure 8. The sub-system of EAF in MATLAB

To use the specifications shown here in Table 1, the four distinct configurations of an AF are explored and the outcomes have been presented in Figures 9-12. The V_{arc} , a V_{pcc} as well as the I_{arc} have been seen in each figure. All current waveforms in figures have been sized to 200 to align the waveform of the voltage. The harmonic V_{arc} , I_{arc} , and V_{pcc} elements by each structure have been seen in Table 2. The dynamic arrangement of an EAF must be analyzed in analysis to define the flicker presented by EAF on the PCC bus.

The dynamic approach is founded on alterations in I_{arc} . The nonlinear as well as time-variable attributes of the length of an arc lead to changes in the resistance of the arc and, therefore the curve of the VIA. One reason for selecting an adaptable component would be to produce a justifiable flicker while limiting the variations within slop including its VIA. $V-I$ waveforms of configurations 1-4 are shown in Figures 9-12 serially.

The dynamic VIA is depicted in Figures 13-20 including all configuration. The assessment of the voltage flicker leads to the formulation of the system V_{rms} modification and also the frequency with which the

deviation occurs, therefore the percent voltage flicker, as well as flicker frequency, have become significant [13]. The direct connections, as well as a description of the cyclic voltage flicker, have been mentioned throughout the reference [13]. Out of the estimations, the percent deviation of $\Delta V/V$ at 10 hertz for 4 setups can be seen in Table 3. It is shown that configurations 3 and 1 have very less deviation as compared to the other 3 AF configurations.




Figure 9. V-I waveform of configuration 1 in a stationary condition




Figure 10. V-I waveform of configuration 2 in a stationary condition




Figure 11. V-I waveform of configuration 3 in a stationary condition




Figure 12. V-I waveform of configuration 4 in a stationary condition

Table 2. Comparative analysis of the harmonics of the varying combinations

Item	Harmonic (%)	Configuration 1	Configuration 2	Configuration 3	Configuration 4
Arc current	Fund, (kA)	77.226	81.824	80.727	65.56
	3 rd	0.1846	0.15068	0.13644	0.20636
	5 th	0.06081	0.05095	0.043556	0.07135
	7 th	0.02577	0.02125	0.017429	0.0319707
	9 th	0.01221	0.012324	0.0091264	0.0162088
	11 th	0.00716	0.009785	0.0072054	0.0095027
Arc voltage	Fund, (V)	398.11	362.7	391.3432	407.1365
	3 rd	0.3571	0.35842	0.301321	0.364177
	5 th	0.1954	0.21053	0.158682	0.213650
	7 th	0.1247	0.1412	0.09551	0.147125
	9 th	0.08625	0.10191	0.060519	0.11298
	11 th	0.06259	0.07885	0.03832	0.09348
Voltage at PCC	Fund, (V)	539.5	534.738	536.387	542.9
	3 rd	0.03349	0.030949	0.02805	0.034536
	5 th	0.01853	0.018317	0.015553	0.0204236
	7 th	0.01182	0.012202	0.010111	0.014127
	9 th	0.00811	0.008688	0.007121	0.01083
	11 th	0.00581	0.006709	0.005253	0.008902




Figure 13. VIA of configuration 1 in dynamic condition




Figure 14. VIA of configuration 2 in dynamic condition




Figure 15. VIA of configuration 3 in dynamic condition




Figure 16. VIA of configuration 4 in dynamic condition




Figure 17. VIA of configuration 2 with R_l modulation




Figure 18. V_{pcc} with $M=0.3$ for R_l




Figure 19. VIA of configuration 2 with R_2 modulation




Figure 20. V_{pcc} with $M=0.3$ for R_2

Table 3. $\frac{\Delta V}{V}$ % at frequency 10 Hz for arc sinusoidal differences

Sr. No.	Configuration type	$\frac{\Delta V}{V}$ (%)
1	Configuration 1	0.2207
2	Configuration 2	0.5956
3	Configuration 3	0.00887
4	Configuration 4	3.047

4. CONCLUSION

TD configuration seems better because frequency domain configuration relies on assumptions that aren't always true. TD-based AF architectures investigated these effects with V-I attributes categorization. The first and fourth configurations lack the data needed to model the third section and respond appropriately. AF differs from configurations first and fourth. Simulation and numerical results show configurations 2 and 3 are better for minimum 3rd harmonics for I_{arc} , V_{arc} , and PCC voltage. This method uses active AF flicker computations. Configuration 1 includes R_{arc} optimization. In evaluating the V_{pcc} waveform for modulation using the computation modulation constants, the authors conclude that using R_2 variation to generate a dynamic response of a furnace causes additional flicker and that the results are consistent with the real one. The furnace gives VIC part AB extra time, but R_1 modulation causes flickering. This novel setup is reliable regardless of the load's state of operation because the AF's energy transfer to the load has been isolated.




REFERENCES

- [1] A. A. Nikolaev, P. G. Tulupov, and O. V. Tulupova, "Melting stage diagnostic in different types of electric arc furnaces based on the analysis of the harmonic composition of the electric arc current," in *2019 8th International Conference on Modeling Simulation and Applied Optimization (ICMSAO)*, pp. 1-6, Apr. 2019, doi: 10.1109/icmsao.2019.8880402.
- [2] W. Ting, "A new frequency domain method for the harmonic analysis of power systems with arc furnace," in *APSCOM-97. International Conference on Advances in Power System Control, Operation and Management*, pp. 552-555, 1997, doi: 10.1049/cp:19971894.
- [3] O. Ozgun and A. Abur, "Development of an arc furnace model for power quality studies," in *199 IEEE Power Engineering Society Summer Meeting. Conference Proceedings (Cat. No.99CH36364)*, doi: 10.1109/pess.1999.784402.
- [4] A. R. Gidd, A. D. Gore, S. B. Jondhale, O. V. Kadekar, and M. P. Thakre, "Modelling, Analysis and Performance of a DSTATCOM for Voltage Sag Mitigation in Distribution Network," in *2019 3rd International Conference on Trends in Electronics and Informatics (ICOEI)*, pp. 366-371, Apr. 2019, doi: 10.1109/icoei.2019.8862554.
- [5] O. Ozgun and A. Abur, "Flicker study using a novel arc furnace model," *IEEE Transactions on Power Delivery*, vol. 17, no. 4, pp. 1158-1163, Oct. 2002, doi: 10.1109/tpwrd.2002.804013.
- [6] S. Varadan, E. B. Makram, and A. A. Girgis, "A new time domain voltage source model for an arc furnace using EMTP," *IEEE Transactions on Power Delivery*, vol. 11, no. 3, pp. 1685-1691, Jul. 1996, doi: 10.1109/61.517535.
- [7] C. Sharmela, G. Uma, M. R. Mohan, and K. Karthikeyan, "Voltage flicker analysis and mitigation - case study in ac electric arc furnace using PSCAD/EMTDC," in *2004 International Conference on Power System Technology, 2004*, 2004, pp. 707-712, doi: 10.1109/icpst.2004.1460084.
- [8] M. Klimas and D. Grabowski, "Application of Shallow Neural Networks in Electric Arc Furnace Modeling," *IEEE Transactions on Industry Applications*, vol. 58, no. 5, pp. 6814-6823, Sep. 2022, doi: 10.1109/tia.2022.3180004.
- [9] T. Zheng and E. B. Makram, "An adaptive arc furnace model," *IEEE Transactions on Power Delivery*, vol. 15, no. 3, pp. 931-939, Jul. 2000, doi: 10.1109/61.871355.




- [10] G. C. Montanari, M. Loggini, L. Pitti, E. Tironi, and D. Zaninelli, "The effects of series inductors for flicker reduction in electric power systems supplying arc furnaces," in *Conference Record of the 1993 IEEE Industry Applications Conference Twenty-Eighth IAS Annual Meeting*, 1993, pp. 1496-1503, doi: 10.1109/ias.1993.299209.
- [11] D. S. Maurya, P. D. Jadhav, R. S. Joshi, R. R. BendkhaLe, and M. P. Thakre, "A Detailed Comparative Analysis of Different Multipulse and Multilevel Topologies for STATCOM," in *2020 International Conference on Electronics and Sustainable Communication Systems (ICESC)*, pp. 1112-1117, Jul. 2020, doi: 10.1109/icesc48915.2020.9155708.
- [12] G. C. Montanari, M. Loggini, A. Cavallini, L. Pitti, and D. Zaninelli, "Arc-furnace model for the study of flicker compensation in electrical networks," *IEEE Transactions on Power Delivery*, vol. 9, no. 4, pp. 2026-2036, 1994, doi: 10.1109/61.329535.
- [13] B. Behera, K. C. Rout, and R. N. Dash, "Voltage Flicker Mitigation Using VSC-Based STATCOM to Improve Power Quality," in *2021 1st International Conference on Power Electronics and Energy (ICPEE)*, pp. 1-5, Jan. 2021, doi: 10.1109/icpee50452.2021.9358667.
- [14] L. Tang, S. Kolluri, and M. F. McGranaghan, "Voltage flicker prediction for two simultaneously operated AC arc furnaces," in *Proceedings of 1996 Transmission and Distribution Conference and Exposition*, 1996, pp. 255-262, doi: 10.1109/tdc.1996.545944.
- [15] A. Singh, R. K. Singh, and A. K. Singh, "Voltage sag correction in distribution system containing a real three phase electric arc furnace," in *2017 4th IEEE Uttar Pradesh Section International Conference on Electrical, Computer and Electronics (UPCON)*, pp. 21-26, Oct. 2017, doi: 10.1109/upcon.2017.8251016.
- [16] A. J. U-Farfan, J. A. O-Wilches, A. I. N-Villota, D. M. V. S-Gutierrez, and E. A. C-Plata, "Evaluation of Protection Systems in Electric Arc Furnaces: A Methodology for Assessment," *IEEE Industry Applications Magazine*, vol. 27, no. 2, pp. 18-35, Mar. 2021, doi: 10.1109/mias.2020.3024481.
- [17] M. P. Thakre and N. P. Matala, "Alleviation of Voltage Sag-Swell by DVR Based on SVPWM Technique," in *2020 International Conference on Power, Energy, Control and Transmission Systems (ICPECTS)*, pp. 1-6, Dec. 2020, doi: 10.1109/icpects49113.2020.9336972.
- [18] G. Singh and C. Miller, "Flicker Source Detection using Correlation Coefficients," in *2020 IEEE PES Innovative Smart Grid Technologies Europe (ISGT-Europe)*, pp. 950-954, Oct. 2020, doi: 10.1109/isgt-europe47291.2020.9248876.
- [19] M. M. Islam and A. H. Chowdhury, "Comparison of dynamic resistance arc furnace models for flicker study," in *2012 7th International Conference on Electrical and Computer Engineering*, pp. 193-196, Dec. 2012, doi: 10.1109/icece.2012.6471518.
- [20] A. A. Nikolaev, P. G. Tulupov, and A. V. Anufriev, "Assessing the feasibility of electrical mode control of ultra-high power arc steelmaking furnace based on data about harmonic composition of arc currents and voltages," in *2015 16th International Conference on Research and Education in Mechatronics (REM)*, pp. 301-308, Nov. 2015, doi: 10.1109/rem.2015.7380411.
- [21] A. Nikolaev, A. Denisevich, and L. Antropova, "An Improved Approach to Defining of Rated Power of Static Var Compensator for Electric Arc Furnace," in *2019 International Russian Automation Conference (RusAutoCon)*, pp. 1-8, Sep. 2019, doi: 10.1109/rusautocon.2019.8867701.
- [22] I. A. Yakimov and V. L. Gorokhov, "Improving efficiency of ultra-high power arc furnaces with thyristor control voltage of furnace transformer," in *2016 2nd International Conference on Industrial Engineering, Applications and Manufacturing (ICIEAM)*, pp. 1-5, 2016, doi: 10.1109/icieam.2016.7910894.
- [23] Y. Wang, Z. Mao, Y. Li, H. Tian, and L. Feng, "Modeling and parameter identification of an electric arc for the arc furnace," in *2008 IEEE International Conference on Automation and Logistics*, pp. 740-743, Sep. 2008, doi: 10.1109/ical.2008.4636247.
- [24] T. S. Barhate and M. P. Thakre, "Generator LOE Protection by Using Offset Mho Relay in the Presence of STATCOM," in *2020 IEEE First International Conference on Smart Technologies for Power, Energy and Control (STPEC)*, pp. 1-6, Sep. 2020, doi: 10.1109/stpec49749.2020.9297745.
- [25] G. C. Lazaroiu, N. Golovanov, L. Elefterescu, D. Zaninelli, and M. Roscia, "Flicker monitoring campaign in EAF facilities equipped with STATCOM," in *2016 17th International Conference on Harmonics and Quality of Power (ICHQP)*, pp. 998-1002, Oct. 2016, doi: 10.1109/ichqp.2016.7783407.
- [26] M. P. Thakre and P. S. Borse, "Analytical Evaluation of FOC and DTC Induction Motor Drives in Three Levels and Five Levels Diode Clamped Inverter," in *2020 International Conference on Power, Energy, Control and Transmission Systems (ICPECTS)*, pp. 1-6, Dec. 2020, doi: 10.1109/icpects49113.2020.9337015.
- [27] S. EswaraRao, B. P. Muni, P. Jain, C. P. V. K. Reddy, and P. V. Balasubramanyam, "Development of 2.5MVAR STATCOM for arc furnace applications," in *2012 IEEE International Conference on Power Electronics, Drives and Energy Systems (PEDES)*, pp. 1280-1285, Dec. 2012, doi: 10.1109/pedes.2012.6484432.
- [28] S. Calligaro and R. Petrella, "Digital Current Control of Electric Arc Furnace by Parallel Modular Three-Phase IGBT Inverters," in *2019 IEEE Applied Power Electronics Conference and Exposition (APEC)*, pp. 1963-1970, Mar. 2019, doi: 10.1109/apec.2019.8722076.

BIOGRAPHIES OF AUTHORS






Dr. Mohan P. Thakre    received the B.Tech. and M.Tech. degrees in Electrical Power Engineering from Dr. Babasaheb Ambedkar Technological University (Dr. BATU), Maharashtra, India, in 2009 and 2011 respectively, and the Ph.D. degree in Electrical Engineering from Visvesvaraya National Institute of Technology (VNIT), Nagpur, Maharashtra, India in 2017. Currently, he is an Associate Professor at the Department of Electrical Engineering, SVERIS College of Engineering, Pandharpur, Maharashtra, India. His research interests include FACTS and power system protection. He can be contacted at email: mohanthakre@gmail.com.






Dr. Pawan C. Tapre    received the B.E. and M.E. degrees in Electrical Power System Engineering from Sant Gadge Baba Amravati University (SGBAU), Maharashtra, India, in 1995 and 2002 respectively, and a Ph.D. degree in Electrical Engineering from Dr. C.V. Raman University (Dr. CVRU), Bilaspur, Chhattisgarh, India in 2022. Currently, he is an Assistant Professor at the Department of Electrical Engineering, S.N.D. College of Engineering and Research Center, Yeola (Nashik), Maharashtra, India. His research interests include deregulated power systems, FACTS, power systems, and power system protection. He can be contacted at email: pawan.tapre73@gmail.com.






Dr. Deepak Prakash Kadam    received a B.E. from the Government College of Engineering, Amaravati, and M.E. degrees in Electrical Power Systems from Walchand College of Engineering, Sangli, Maharashtra, India, in 1997 and 2005 respectively, and the Ph.D. degree in Electrical Engineering from Savitribai Phule Pune University, Pune Maharashtra, India in 2015. Currently, he is an Associate Professor at the Department of Electrical Engineering, Bhujbal Knowledge City, MET Institute of Engineering, Nashik, India. His research interests include renewable energy technology, power quality, and power system. His total teaching experience is around 23 years. He can be contacted at email: dpkadam@gmail.com.






Mr. Mousam Sharma    received the B.Tech. degree in Electrical Engineering from MP Christian College of Engineering & Technology, Bhilai in 2006 and M.Tech. degree in Instrumentation and Control from Bhilai Institute of Technology Durg, Chhattisgarh, India, in 2013 and the Ph.D. degree pursuing in electrical engineering from C. V. Raman University, Kota, (CVRU), Bilaspur, Chhattisgarh, India. Currently, he is an Assistant Professor at the Department of Electrical & Electronics Engineering, Bhilai Institute of Technology, Durg, India. His research interests include flexible AC transmission systems (FACTS) and power system protection. He can be contacted at email: elec.mousam786@gmail.com.



Dr. Sunil Somnath Kadlag    received B.E. in Electrical Engineering from Dr. Babasaheb Ambedkar Marathwada University, Aurangabad (Dr B.A.M.U) in 1997 and M.E. in Electrical Engineering (Control System) from Government College of Engineering Pune (Pune University) in 2005 and Ph.D. in Electrical Engineering from Suresh Gyan Vihar University Jaipur (Rajasthan) in 2021. His research area is electric vehicles. He is presently working as an Associate Professor and Head, of the Department of Electrical Engineering, Amrutvahini College of Engineering, Sangamner, Savitribai Phule Pune University, Pune, Maharashtra, India. He can be contacted at email: sunilkadlag5675@gmail.com.



Dr. Yogesh Vilas Mahadik    received the B.Tech., M.Tech., and Ph.D. degrees in Electrical Power Engineering from Dr. Babasaheb Ambedkar Technological University (Dr. BATU), Maharashtra, India, in 2008, 2011, and 2020 respectively. Currently, he is a lecturer at the Department of Electrical Engineering, Government Polytechnic Malvan, Maharashtra, India. His research interests include energy management in EVs and electrical machines. He can be contacted at email: yogi_maha@yahoo.co.in.